






collingwood

01604 495 151  
collingwoodlighting.com

-  collingwoodled
-  /collingwoodlighting
-  collingwoodlighting

# Microwave Sensor

Motion sensor with daylight threshold switch

## Guarantee

5 years

## Features

IP rating	IP65
Dimmable Option	Yes (0-10V and PWM)

## Installation information

Install Connector Type	Zhaga Book 18
Weight	0.03
Maximum Ambient Temperature	-20°C to +60°C

## Features & benefits

Plugs into the centre of the Area Bay luminaire using the Zhaga socket

Typical installation height 8-13m

Hold time  
Default is 5 seconds  
Options -  
30s/1min/3min/5min/10min/20min/30min

Stand-by dimming level  
Default is 10%  
Options - 20%/30%/50%

Stand-by period  
Default is 0 seconds  
Options -  
10s/30s/1min/5min/10min/30min

Daylight threshold  
Default is 'disable'  
Options -  
2Lux/10Lux/30Lux/50Lux  
120Lux/200Lux/250Lux  
300Lux/350Lux/400Lux

## Accessories

Area Bay	High bay product range	Sold Separately
----------	------------------------	-----------------

## PRODUCT CODES

	Finish	Description
HBMWS	Matt black RAL9017	Microwave motion sensor with daylight threshold switch